
## APPROVAL SPECIFICATIONS

CUSTOMER	CUSTOMER'S P/N	GYE'S P/N	PRODUCT	REVISION
		KAN1211	TACT SWITCH	А

#### A. Specification & meanings

The name of the tact switch is composed by type and specification, the particular meaning of the type, specification and code is as follows.



1. Product height: It is denoted by three figures; For examples, "075" expresses the product which the total height is 7.5mm, as chart 1 shows:

Code	Product height	Code	Product height	Code	Product height
043	4.3	090	9	170	17
050	5	095	9.5		
060	6	100	10		
070	7	110	11		
075	7.5	120	12		
080	8	130	13		
085	8.5	150	15		

2. Stem color: It is expressed by a figure, as chart 2 shows:

Color	Black
Code	1

3. Operating force: An English letter expresses it, unite: Newton (N), as chart 3 shows:

force Code Spe	Operating ec	Press force	Return force	
Α	1.0	1.0±0.3	0.2min	
В	1.6	1.6±0.5	0.4min	
С	2.6	2.6±0.5	0.6min	

Examples: "KAN1211-0501B" denotes the tact switch with  $12\times12$  base, the height is 5mm,the stem is black, the operating force is 1.6N.

APPROVE BY 杨过 09.10.25 CHECKED BY	关 林 09.10.25	PRPARE BY	曹 盖 09.10.25
-----------------------------------	--------------	-----------	--------------

## **APPROVAL SPECIFICATIONS**

CUSTOMER	CUSTOMER'S P/N		PRODUCT	REVISION	
		KAN1211	TACT SWITCH	А	

1、 概述

**GENERAL** 

1.2 适用范围

#### **APPLICATION**

此规格书适用于机械式轻触开关的相关要求

This specification is applied to the requirements for TACTILE SWITCH (MECHANICAL CONTACT)

1.3 工作温度范围

#### Operating Temperature Range

- -20℃~70℃(在标准大气压、标准湿度条件下)
- -20°C ~70°C (Normal humidity, normal air pressure)
- 1.4 贮藏温度范围

#### Storage Temperature Range

- -30℃~80℃(在标准大气压、标准湿度条件下)
- -30  $^{\circ}$ C  $^{\circ}$ 80  $^{\circ}$ C (Normal humidity, normal air pressure)
- 1.5 测试条件

#### **Test Conditions**

在没有其它特定的条件下,应该在以下的条件下进行测试和测量:

Unless otherwise specified, tests and measurement shall be made in the following standard conditions:

常温......5℃~35℃

Normal temperature......5℃~35℃ 标准湿度......

......相对湿度 25%~85% Normal

humidity.....relative humidity 25%~85% 标准大

气压......86KPa~106Kpa

Normal air pressure......86Kpa~106Kpa

在制造过程中,测试和测量应该在以下的条件下进行:

If any doubt arise from the judgment, tests shall be conducted at the following conditions:

Relative humidity......65%±5%

环境气压......86KPa~106Kpa Air pressure......86KPa~106Kpa

 APPROVE BY
 杨过 09.10.25
 CHECKED BY
 关 林 09.10.25
 PRPARE BY
 曹 盖 09.10.25

## APPROVAL SPECIFICATIONS

CUSTOMER	CUSTOMER'S P/N	GYE'S P/N	PRODUCT	REVISION
		KAN1211	TACT SWITCH	А

2、 详细说明

Detailed specification

2.1 外观:应无影响、降低产品性能的缺陷;

Appearance: There should be no defects that affect the serviceability of product.

2.2 结构尺寸和安装尺寸:应符合装配图要求;

Style and dimension: shall conform to the assemble drawings.

2.3 操作形式:有触觉反应的操作

Type of actuating: Tactile feedback.

2.4 开关结构: 单回路单输出(具体的触点结构在装配图中已绘出);

Contact arrangement: 1 pole, 1 throw

(Details of contact arrangement are given in the assembly drawings.)

2.5 开关工作额定值: DC 12V, 50mA (有效值)

Ratings: 12V DC, 50mA (effective value)

3. 电气性能:

**ELECTRICAL SPECIFICATION** 

项	目			要求		
	ΞM		TE	REQUIREMENTS		
1		接触电阻 act Resistance	在以 5V 10mA 的源 的电路中,以一个等于 Applying a static the center of the stem 5V DC 10mA or mo	≪50mΩ		
2	I	绝缘电阻 Insulation Resistance	在端子之间施加 D 之间底座、盖板的电阻 Measurement sha 100V DC potential, terminals and cover, fo	≥100MΩ		
3	Die	广质耐压 electric tage proof	在端子之间施加 250V AC(50HZ 或 60HZ)/1min 250V AC (50HZ or 60HZ) shall be applied across terminals, for one minute.			无击穿、无飞弧 There should be no breakdown and flashover
APPROVE BY 杨过 09.10.25			5 CHECKED BY	关 林 09.10.25	PRPARE B	Y 曹 盖 09.10.25

## **⊚** TACTRONIC

# APPROVAL SPECIFICATIONS

CUSTOMER	CUSTOMER'S P/N	CUSTOMER'S P/N GYE'S P/N PRODUCT		REVISION
		KAN1211	TACT SWITCH	А
项目		试验条件		要求
ITEM	-	TEST CONDITIONS		REQUIREMENTS
触点抖 Bound	按照正常使用时的力度 在导通和断开过程中犯 Lightly striking the cel	nter of the stem at a rat times per second), and FF"	e encountered in bounce shall be	DN-3msec.max DFF-8msec.max
	"导通" " ON"	" 断开" "OFF"		

#### MECHANICAL SPECIFICATION

IVILOI	WECHANICAL SPECIFICATION								
1	按力 Operating Force	量开关导通所需 Placing the sw vertical and th center of the s	开关垂直于操作方向放置,在开关驱动件顶端中心逐渐施力,测量开关导通所需的最大力度。 Placing the switch such that the direction of switch operation is vertical and then gradually increasing the load applied to the center of the stem, the maximum load required for the switch to come to a stop shall be measured.						
2	最大行程 Full Travel	开关驱动件顶端 Placing the sw vertical and the the center of th	开关垂直于操作方向放置,以一个等于 2 倍接力的静负荷施加在 开关驱动件顶端中心,测量顶端移动的距离。 Placing the switch such that the direction of switch operation is vertical and then applying static load of 2times operating force to the center of the stem; the travel distance for the switch to come to a stop shall be measured.						
APP	ROVE BY	杨过 09.10.25	CHECKED BY	关 林 09.10.25	PRPARE	BY	曹 盖 09.10.25		



_			/ \1 1	INOVAL	OI L	-011 10	<i>,</i> , , ,	0110
С	USTOMER	CUSTOMER'S	P/N GY	E'S P/N	Pl	RODUCT		REVISION
			K	AN1211	TAC	CT SWITCH		Α
	项目		试 验	条件				要求
	ITEM		TEST CO	NDITIONS			RE	QUIREMENTS
3	回弹力 Return Forc	开关垂直于操作 后,测量顶端向 The sample sw operation is ver to the whole tra	开关垂直于操作方向放置,在开关驱动件顶端中心下降至全行程后,测量顶端向自由位置转换的力度。 The sample switch is installed such that the direction of switch operation is vertical and upon depressing the stem in its center to the whole travel distance, the force of the stem to return to its free position shall be measured.					fer to chart 3
4	停止强度 Stop Streng	荷持续 1min。 th Placing the swit vertical, and the	开关垂直于操作方向放置,从操作方向向驱动件施加 30N 的静负荷持续 1min。 Placing the switch such that the direction of switch operation is vertical, and then a static load of 30N shall be applied in the direction of stem operation for a period of 1 min.					和电气损坏 There no sign of damage chanically and electrically.
5	手柄拔出 强度 Stem Strength	的行程范围。 Placing the swit vertical, and the	开关垂直于操作方向放置,反方向实施最大操作力,并测量手柄的行程范围。 Placing the switch such that the direction of switch operation is vertical, and then the maximum force to withstand a pull applied opposite to the direction of stem operation shall be measured.					20N.min.
6	在以下设定条件下进行测量: Measurements shall be made following the test set forth below: (1) 焊接温度:245±5℃ Solder temperature: 245±5℃ (2) 浸入时间:2s±0.5s Immersion time: 2s±0.5s 对于其它步骤参考《GB 5095.6—86》试验 12a The other steps please refer to《GB 5095.6-86》TEST 12a					9 E c n	00%以⅃ Except	for the edge, the should cover a
APP	ROVE BY	杨过 09.10.25	CHECKED BY	关 林 09	.10.25	PRPARE	BY	曹 盖 09.10.25

## **©** TACTRONIC

С	USTOMER		CUSTOMER	'S P/N	GYE'	S P/N	PR	ODUCT		REVISION
					KAN	1211	TAC	T SWITCH		А
	项目				试 验	条件				要求
	ITEM				TEST CON	NDITIONS			RE	QUIREMENTS
	限电气性能: RONMENTAL	. SPEC	CIFICATION							
1	低温测试 Resistance low tempera	to iture	标准湿度的 Following to normal tern measureme (1) 温度 Tem (2) 时间	Temperature : -30±2℃					Contac ≤200m! 项目 3,	
2	高温测试 Heat resista	nce	标准湿度的 set forth below humidity co (1) 温度 tem (2) 时间	forth below the sample shall be left in normal temperature and humidity conditions for 1 h before measurements are made:  (1) 温度: 80±2℃ temperature:80±2℃						⊞: ≤200mΩ t resistance: Ω 4.1,4.2,4.3 4.1,4.2,4.3
3	温度周期性 试 Chang temperati	e of	根据下面的 后 样品应放在 试期间样品 After 5 cyc allowed to conditions	常温及 应保持- cles of stand for 1 h.	8h 要求进行 5 次循环的温度周期性测试, 实验 及标准湿度的环境中 1 小时后做性能测试。测					⊞: ≤200mΩ t resistance: Ω 4.1,4.2,4.3 4.1,4.2,4.3
APPROVE BY 杨过 09.10.25 CHECKED BY				关 林 (	09.10.25	PRPARE	BY	曹 盖 09.10.25		

## **⊚** TACTRONIC

APPROVAL SPECIFICATIONS							CIVO	
C	USTOMER	CUSTOMER'S P/N	GYE'S P/N	F	PRODUCT		REVISION	
			KAN1211 TACT SWITCH				Α	
	项目						要求	
	ITEM		TEST CONDITION	IS		RF	QUIREMENTS	
4	湿温测试 Moisture resistance	标准湿度的环境中 set forth below the sar humidity conditions (1) 温度: 60± temperature (2) 相对湿度: relative hum	forth below the sample shall be left in normal temperature and humidity conditions for 1 h before measurements are made:  (1) 温度: 60±2℃ temperature: 60±2℃  (2) 相对湿度: 90%~95% relative humidity:90% to 95%  (3) 时间: 96h					
5	硫化试验 Sulfuration resistance	标准湿度的环境中 set forth below the sar humidity conditions (1) H2S 气体和 H <sub>2</sub> S gas co (2) 时间: 72h Time: 72h (3) 温度: 40±2	forth below the sample shall be left in normal temperature and humidity conditions for 1 h before measurements are made:  (1) H2S 气体浓度: 3ppm±1ppm H <sub>2</sub> S gas concentration: 3ppm±1ppm (2) 时间: 72h Time: 72h (3) 温度: 40±2℃ (90~95%RH)					
6	盐雾试验 Salt Mist						上没有腐蚀斑点 No remarkable on shall be zed in metal part.	
APP	ROVE BY	杨过 09.10.25 CHE	ECKED BY	09.10.25	PRPARE	E BY	曹 盖 09.10.25	

## **©** TACTRONIC

AFFROVAL SFLOII ICATIONS									
С	CUSTOMER CUSTOME			P/N GYE'	S P/N	Р	RODUCT		REVISION
	KAI				1211	TAC	CT SWITCH		Α
6、极限机械性能: ENDURANCE SPECIFICATION									
	项目			试 验	条 件				要求
	ITEM			TEST CON	IDITIONS			RE	QUIREMENTS
1	工作寿命 Operation		DC 12V, 50 mA resistive load resistance≤2						初值的±30% ng Force: alue±30% 4.1,4.2,4.3
2	振动 Vibra	ation	Measurement (1)振动频 Vibra (2)振幅 Ampli (3)振动力 Direct direct (4)测试时	Vibration frequency range: 10 to 55 to 10Hz  (2) 振幅(峰一峰): 1.5mm Amplitude: 1.5mm  (3) 振动方向: 包括手柄行程方向在内的三个相互垂直的方向 Direction of vibration:Three mutually perpendicular direction including the direction of stem travel					4.1,4.2,4.3 1.1,4.2,4.3
7. 焊接条件: SOLDERING CONDITIONS:									
			请按↓	以下条件进行焊接	:				
				旱锡温度:≤350℃					
	4 十/旧位			F 協 ᇤ 反: ▽ 550 ℃ E 续焊接时间: ≤ 3					
7.1	手工焊接 Hand solde	ering	, ,	se practice accord		condition	ons:		
(1) Soldering temperature: 350°C Max. (2) Continuous soldering time: 3 s Max.									
APPROVE BY 杨过 09.10.25 CHECKI			CHECKED BY	关 林 09	.10.25	PRPARE	ΕBY	曹 盖 09.10.25	

## APPROVAL SPECIFICATIONS

Cl	CUSTOMER CUSTOMER'S P/N		GYE'S P/N		PRODUCT	REVISION		
			KA	AN1211	TACT SWITCH	А		
	自动浸焊	项目 Items	s 条件 Condition					
	Conditions for	助焊剂附着量		不附着于零部	3件贴装面的程度			
	Auto-dip	Flux built-up	uilt-up Mounting surface should not be coated with flax					
		预热温度 Preheating temper	预热温度 Preheating temperature		印刷电路板焊接面的周围温度 100℃ max. Ambient temperature of the soldered surface of PC board. 100℃ max.			
7.2		预热温度时间 Preheating tim	预热温度时间 Preheating time		60s max.			
		焊接温度 Soldering temperature			260℃ max.			
		焊接浸渍时间 Continuous dipping	g time	5s max.				
	焊接次数		2 次以下					
		Number of solde	ering	2times max.				

#### 焊接说明:

1、开关浸焊后,注意不要用溶剂清洗。

After switches were soldered, please be careful not to clean switches with solvent.

1.1 在使用烙铁的情况下,焊锡温度应在 350℃以下、3 秒以内。

In the case of using solding iron, solding conditions shall be 350℃ max and 3 sec.max.

1.2 浸焊后,注意不要在顶部施加负荷。

Right after switches were soidered; please be careful not to load to on the knobs of switches.

- 2、设计中应注意的事项( Design instructions)
- 2.1 印刷基板的安装孔尺寸参见产品图。

Follow recommended P.W.B. piercing plan in outside drawing page.

- 3、注意点(Note):
- 3.1 注意不要施加超负荷的压力或晃动开关。

Please be cautions not to give excessive static load or shock to swiches.

3.2 开关浸焊后,印刷基板注意不要叠放。


Please be careful not to pile up P.W.B.after switches were soldered.


**3.3** 保管时尤其应注意避开高湿高温和有腐蚀性气体的环境。如需要长时间保存,请不要打开包装箱。


Preservation under high temperature and high high humidity or corrosive gas should be avoided Especially. When you need to preserve for a long period ,do not open the carton.


APPROVE BY	杨过 09.10.25	CHECKED BY	关 林 09.10.25	PRPARE BY	曹 盖 09.10.25
------------	-------------	------------	--------------	-----------	--------------

CUSTOMER	CUSTOMER'S P/N	GYE'S P/N	PRODUCT	REVISION
		KAN1211	TACT SWITCH	А











NO.	NAME	MATERIAL	NATIONALITY	QTY.	FINISHING
1	TERMINAL	Brass	China	1	Silver plating
2	CASE	PA66-G30	China	1	Black
3	CONTACT	Phosphor bronze	Korea	1	Contact side silver plating
4	COVER	SPCC-SD	China	1	CuSn plating
5	STEM	PA66-G30	China	1	Black

APPROVE BY	杨过 09.10.25	CHECKED BY	关 林 09.10.25	PRPARE BY	曹 盖 09.10.25
------------	-------------	------------	--------------	-----------	--------------

# **APPROVAL SPECIFICATIONS**

CUSTOMER	CUSTOMER'S P/N	GYE'S P/N	PRODUCT	REVISION
		KAN1211	TACT SWITCH	А

8. 生产工场: The country of origin

WENZHOU GANGYUAN ELECTRONICS CO.,LTD
NO.392 NING KANG EAST ROAD OF YUE QING CITY, ZHE JIANG

9. 包装: Packing

产品规格	包装袋 PACKING BAG		内包装箱 INTER BOX		外包装箱 OUT BOX		净重	毛重
KAN1211	规 格(Cm)	数量(pcs)	规 格(Cm)	袋数	规 格(Cm)	盒数	(Kg)	(Kg)
043	19×21	500	$21.6 \times 16.5 \times 6.1$	2	$44.5 \times 35 \times 28$	16	11.7	13.811
050	19×21	500	$21.6 \times 16.5 \times 6.1$	2	$44.5 \times 35 \times 28$	16	12.6	14.711
060	19×21	500	$21.6 \times 16.5 \times 6.1$	2	$44.5 \times 35 \times 28$	16	13.5	15.611
070	19×21	500	$21.6 \times 16.5 \times 6.1$	2	$44.5 \times 35 \times 28$	16	13.9	16.011
075	19×21	500	$21.6 \times 16.5 \times 6.1$	2	$44.5 \times 35 \times 28$	16	14.5	16.611
080	19×21	500	$21.6 \times 16.5 \times 6.1$	2	$44.5 \times 35 \times 28$	16	14.8	16.911
085	19×21	500	$21.6 \times 16.5 \times 6.1$	2	$44.5 \times 35 \times 28$	16	15.0	17.111
090	19×21	500	$21.6 \times 16.5 \times 6.1$	2	$44.5 \times 35 \times 28$	16	15.4	17.511
095	19×21	500	$21.6 \times 16.5 \times 6.1$	2	$44.5 \times 35 \times 28$	16	16.2	18.311
100	19×21	500	$21.6 \times 16.5 \times 6.1$	1	$44.5 \times 35 \times 28$	16	8.16	10.168
110	19×21	500	$21.6 \times 16.5 \times 6.1$	1	$44.5 \times 35 \times 28$	16	8.32	10.328
120	19×21	500	$21.6 \times 16.5 \times 6.1$	1	$44.5 \times 35 \times 28$	16	8.85	10.858
130	19×21	500	$21.6 \times 16.5 \times 6.1$	1	$44.5 \times 35 \times 28$	16	9.20	11.208
150	19×21	500	$21.6 \times 16.5 \times 6.1$	1	$44.5 \times 35 \times 28$	16	9.35	11.358
170	19×21	500	$21.6 \times 16.5 \times 6.1$	1	$44.5 \times 35 \times 28$	16	9.89	11.898

APPROVE BY	杨过 09.10.25	CHECKED BY	关 林 09.10.25	PRPARE BY	曹 盖 09.10.25
------------	-------------	------------	--------------	-----------	--------------