



Constant voltage design

Universal AC input / Full range

Withstand 300VAC surge input for 5 seconds

Protections: Short circuit / Overload / Over voltage

Cooling by free air convection

Fully encapsulated with IP67 level (Note.9)

Fully isolated plastic case

Class II power unit, no FG

Class 2 power unit

Pass LPS

Suitable for LED related fixture or appliance

(such as LED Decoration or Advertisement devices)(Note.8) 00% full load burn-in test

ow cost, high reliability

warranty 2 years warranty

□ LPS IP67 : SUs CBCE

SPECIFIC MODEL		LPV-35-5	LPV-35-12	LPV-35-15	LPV-35-24	LPV-35-36	
IVODEL	DO VOLTA OF						
OUTPUT	DC VOLTAGE	5V	12V	15V	24V	36V	
	RATED CURRENT	5A	3A	2.4A	1.5A	1A	
	CURRENT RANGE	0 ~ 6A (Note.7)	0~3A	0~2.4A	0 ~ 1.5A	0~1A	
	RATED POWER	30W	36W	36W	36W	36W	
	RIPPLE & NOISE (max.) Note.2		120mVp-p	120mVp-p	150mVp-p	150mVp-p	
	VOLTAGE TOLERANCE Note.3						
	LINE REGULATION	±1.0%					
	LOAD REGULATION	±4.0%	±2.0%				
	*	5 500ms, 20ms / 230VAC 500ms, 20ms / 115VAC at full load					
	HOLD UP TIME (Typ.)	50ms/230VAC 16ms/115VAC at full load					
INPUT		90 ~ 264VAC 127 ~ 370VDC					
	FREQUENCY RANGE	47 ~ 63Hz		200	950	250	
	EFFICIENCY (Typ.)	77%	84%	84%	85%	85%	
	AC CURRENT (Typ.)	1.1A/115VAC 0.7A/230VAC					
	INRUSH CURRENT(Typ.)	COLD START 55A(twidth=510µs measured at 50% lpeak) at 230VAC					
	MAX. No. of PSUs on 16A CIRCUIT BREAKER	4 units (circuit breaker of type B) / 7 units (circuit breaker of type C) at 230VAC					
	LEAKAGE CURRENT	0.25mA / 240VAC					
PROTECTION	OVERLOAD	110 ~ 150% rated output power					
	OVLITEOAD	Protection type: Hiccup mode, recovers automatically after fault condition is removed					
	OVER VOLTAGE	5.75 ~ 6.75V	13.8 ~ 16.2V	17.25 ~ 20.25V	27.6 ~ 32.4V	41.4 ~ 48.6V	
		Protection type: Shut down o/p voltage, re-power on to recover					
ENVIRONMENT	WORKING TEMP.	-30 ~ +65°C (Refer to "Derating Curve")					
	WORKING HUMIDITY	20 ~ 90% RH non-condensing					
	STORAGE TEMP., HUMIDITY	-40 ~ +80°C, 10 ~ 95% RH					
	TEMP. COEFFICIENT	±0.03%°C (0 ~ 50°C)					
	VIBRATION	10 ~ 500Hz, 2G 10min./1cycle, period for 60min. each along X, Y, Z axes					
SAFETY& EMC	SAFETY STANDARDS	UL1310 class 2, CAN/CSA No. 223-M91, IP67 approved; design refer to TUV EN60950-1					
	WITHSTAND VOLTAGE	I/P-O/P:3KVAC					
	ISOLATION RESISTANCE	I/P-O/P:>100MOhms/500VDC/25°C/70%RH					
	EMC EMISSION	Compliance to EN55032 (CISPR32) Class B, EN61000-3-2 Class A, EN61000-3-3					
	EMC IMMUNITY	Compliance to EN61000-4-2,3,4,5,6,8,11, EN55024, light industry level, criteria A					
OTHERS	MTBF	743.5Khrs min. MIL-HDBK-217F (25°C)					
	DIMENSION	148*40*30mm(L*W*H)					
	PACKING	0.34Kg; 40pcs/14.6Kg/0.63CUFT					
NOTE	All parameters NOT special Ripple & noise are measure Tolerance : includes set up Derating may be needed ur The power supply is consided complete installation, the fif Length of set up time is me	lly mentioned are measured at 230VAC input, rated load and 25°C of ambient temperature. and at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf & 47uf parallel capacitor. tolerance, line regulation and load regulation. Inder low input voltage. Please check the static characteristics for more details. Inder low input voltage. Please check the static characteristics for more details. Inder low input voltage in the static characteristics for more details. Inder low input voltage. Please check the static characteristics for more details. Inder low input voltage. Please check the static characteristics for more details. Inder low input voltage. Please check the static characteristics for more details. Inder low input voltage. Please check the static characteristics for more details. Inder low input voltage. Please check the static characteristics for more details. Inder low input voltage. Please check the static characteristics for more details. Inder low input voltage. Please check the static characteristics for more details. Inder low input voltage. Please check the static characteristics for more details. Inder low input voltage. Please check the static characteristics for more details. Inder low input voltage. Inder low input volt					

- 7. LPV-35-5 can provide 6A of output current continuously. Based on the requirement of UL1310 class 2, the output current is only certified up to 5A for the test report of LPV-35-5.

 8. The unit might not be suitable for lighting applications in EU countries. Please check with your local authorities for the possible use of the unit.

 9. Suitable for indoor use or outdoor use without direct sunlight exposure. Please avoid immerse in the water over 30 minute.



